

LED 1.5m tube menu

Address	001-512	Address 001-512	
	5CH	5 channel	
	6CH	6 channel	
	7CH	7 channel	
	12CH	12 channel	
	40CH	40 channel	
	80CH	80 channel	
	160CH	160 channel	
DMX Fail	Hold	DMX512 data hold	
	Blakout	DMX512 data does not hold (black field)	
Dimmer Curve	Curve 1	linear curve	
	Curve 2	square curve	
	Curve 3	logarithmic curve	
	Curve 4	S-curve	
Custom	Red: 0-255	red manual dimming	
	Green: 0-255	Green manual dimming	
	Blue: 0-255	blue manual dimming	
	White: 0-255	white manual dimming	
	Yellow: 0-255	Yellow manual dimming	
Program	Color	DIM:0-255	
		Color:1-27	
		Strobe:0-255	
	Lee Color	Lee Color	DIM:0-255
			L101
			L102
			L105
			L106
			L107
			L110
			L111
			L115
			L116
			L118
			L119
			L121
			L124
			L126
			L127
			L128
L132			
L135			

		L139
		L147
		L151
		L152
		L158
		L164
		L174
		L179
		L180
		L201
		L203
		L204
		Strobe:0-255
CCT		DIM:0-255
	CCT	2700K
		3000K
		3200K
		3500K
		3800K
		4100K
		4400K
		4700K
		5000K
		5300K
		5600K
		5900K
		6200K
		6500K
		6800K
		7100K
		7400K
	7700K	
	8000K	
	8300K	
	8600K	
	8900K	
	9200K	
	9500K	
	9800K	
	10000K	
	10500K	
	11000K	
	11500K	

		12000K
		G/M:-1.00-1.00
HSI		DIM:0-255
		HUE:0-360
		STA:0-100
Auto		Auto Mode:0-68
		Speed:1-16
		Color:0-27
Sound		Sound Mode:0-3
		SENS:1-100
		Color:0-27
WIFI		LED_XXX
Master/Slave	Master	
	Slave	
Wireless DMX	ID1-ID7	
	Off	
Run Time	1h/2h/3h/4h/5h/6h/7h/8h/9h/10h/11h/12h	
Information	Version1.1	
	Current Time 00H35M 00S	
IR	ON	
	OFF	
Menu Lock	ON	
	OFF	
Back Light	Always On	
	10s	
	20s	
	30s	
Factory Reset	ON	
	YES	